

In the Claims:

Please cancel claims 1-30 and add the following new claims:

31. (New) A multiple store buffer forwarding apparatus, comprising:

- a processor having a write combining buffer, and

- a non-volatile memory coupled to the processor, said non-volatile memory storing instructions which when executed by the processor cause the processor to:

- execute a plurality of store instructions referencing a first memory region;

- execute a load instruction referencing a second memory region;

- determine that the second memory region matches a cacheline address;

- determine that the first memory region completely covers the second memory region; and

- transmit a store forward is OK signal.

32. (New) The multiple store buffer forwarding apparatus of claim 31, wherein the write combining buffer includes:

- a comparator to receive and compare an address of the second memory region with all existing cacheline addresses in the write combining buffer,

- an address and data buffer coupled to the comparator,

- a data valid bits buffer coupled to the address and data buffer,

- a multiplexer coupled to the data valid bits buffer, and

- a comparison circuit coupled to the multiplexer.

33. (New) The multiple store buffer forwarding apparatus of claim 32, wherein the multiplexer is to:

- receive a byte valid vector from the data valid bits buffer,

- receive address bits from the load instruction,

- select a group of valid bits from the byte valid vector, and

output the group of valid bits.

34. (New) The multiple store buffer forwarding apparatus of claim 33, wherein the comparison circuit is to:

receive the group of valid bits;

receive an incoming load instruction byte mask;

determine that it is acceptable to forward the data using the group of valid bits and the incoming load instruction byte mask; and

produce a forward OK signal.

35. (New) The multiple store buffer forwarding apparatus of claim 31, wherein said processor is implemented as a multi-processor having associated with each said multi-processor a separate set of hardware resources.

36. (New) A multiple store buffer forwarding apparatus, comprising:

a memory;

a processor coupled to said memory and having a write combining buffer, said processor to

execute a plurality of store instructions referencing a first memory region of said memory;

execute a load instruction referencing a second memory region of said memory;

determine that the second memory region matches a cacheline address;

determine that the first memory region completely covers the second memory region; and

transmit a signal indicating that store buffer forwarding is authorized.

37. (New) The multiple store buffer forwarding apparatus of claim 36, wherein the write combining buffer includes:

a comparator to receive and compare an address of the second memory region with all existing cacheline addresses in the write combining buffer,

an address and data buffer coupled to the comparator,
a data valid bits buffer coupled to the address and data buffer,
a multiplexer coupled to the data valid bits buffer, and
a comparison circuit coupled to the multiplexer.

38. (New) The multiple store buffer forwarding apparatus of claim 36, wherein the multiplexer is to:

receive a byte valid vector from the data valid bits buffer,
receive address bits from the load instruction,
select a group of valid bits from the byte valid vector, and
output the group of valid bits.

39. (New) The multiple store buffer forwarding apparatus of claim 38, wherein the comparison circuit is to:

receive the group of valid bits;
receive an incoming load instruction byte mask;
determine that it is acceptable to forward the data using the group of valid bits and the incoming load instruction byte mask; and
produce a signal indicating that it is acceptable to forward the data.

40. (New) The multiple store buffer forwarding apparatus of claim 36, wherein said processor is implemented as multiple processors wherein a separate set of hardware resources is associated with each of said multiple processors.